

SW Re-flash Guide

Model Supported: ASUS VivoTab™ RT

Version:1.0

Prepared for:

- ASUS Internal Release
- Customer

Prepared by: TF600TG PM Team

Service Team

Engineering Team

1. SW Image Re-flash

1.1. Ensure the Device is in Proper State for SW Image Re-flash

Step 1: Ensure the device has at least 50% battery

Step 2: Plug the USB Dongle (or Keyboard dock) into the device

1.2. Update Modem Firmware

Step 1: Plug the USB Dongle (or Keyboard dock) into the device


Step 2: Plug the Tools USB thumb drive into USB Dongle (or Keyboard dock)

Step 3: Press “Desktop” tile in Start Menu


Step 4: Press “File Explorer” in bottom left corner




Step 5: Press on “Computer” on the left side




Step 6: Long press (or right click if using Keyboard Dock) on “Computer” to and then press “Manage”




Step 7: The Computer Management window will pop out, press “Device Manager” on the left side, and then press “View” in the Menu bar




Step 8: Press “Show hidden devices” under View




Step 9.1: Expand the “Software devices” in the middle, and long press (or right click if using Keyboard Dock) on “Mobile Broadband Firmware Device”. Go to step 10.1.




Step 9.2: Expand the “Firmware” if you **cannot** find “Mobile Broadband Firmware Device” in step 9.1 and long press (or right click if using Keyboard Dock) on “ASUS TF600TG Firmware Update Device”. Go to step 10.2.




Step 10.1: Press “Update Driver Software...” Go to step 11.




Step 10.2: Press “Update Driver Software...”




Step 11: Press “Browse my computer for driver software”




Step 12: Press “Browse” so select the folder modem file is in




Step 13: Navigate to the USB thumb drive and select the folder “__1.2 Update Modem FW”, and then press “OK”



Step 14: Verify the path to search in is “<<USB thumb drive>>:__1.2 Update Modem FW”, and then press “Next”




Step 15: The modem FW will automatically update and show the following screen upon success




1.3. Verify SW Image

Step 1: Double click folder “_1.3 Verify SW Image”


Step 2: Click on “File” in the top left corner of the window



Step 3: Long press on the ‘MODEMCHECK.bat’ and select “Run as administrator”



Step 4: Press “Yes” when Command Prompt’s UAC prompt pops up



Step 5: The script will automatically check to see if all parts of SW flashing process has been complete as intended. Upon success, you will see the following screen.

