

P9X79

DDR3 1866 Qualified Vendors List (QVL)										
Vendors	Part No.	Size	SS/DS	Chip Brand	Chip No.	Timing	Voltage	DIMM socket support (Optional)		
								2 DIMM	4 DIMM	6 DIMM
A.DATA	AX3U1866GC2GBB(XMP)	2GB	SS	-	-	9-11-9-27	1.55-1.75	●	●	●
A.DATA	AX3U1866GC4GBB(XMP)	4GB	DS	-	-	9-11-9-27	1.55-1.75	●	●	●
CORSAIR	CM2BG3M2A1866C9(XMP)	8GB (2x 4GB)	DS	-	-	9-10-9-27	1.5	●	●	●
G.SKILL	F3-14900CL9Q-16GB(XMP)	16GB (4x 4GB)	DS	-	-	9-10-9-28	1.5	●	●	●
G.SKILL	F3-15000CL9Q-4GB(XMP)	4GB(2 x 2GB)	DS	-	-	9-9-9-24	1.65	●	●	●
G.SKILL	F3-14900CL9Q-8GBSR(XMP)	8GB (2x 4GB)	DS	-	-	9-10-9-28	1.5	●	●	●
G.SKILL	F3-14900CL9Q-8GBFLD(XMP)	8GB (2x 4GB)	DS	-	-	9-9-9-24	1.6	●	●	●
KINGSTON	KHX1866C9D3T1K3/3GX(XMP)	3GB (3x 1GB)	SS	-	-	-	1.65	●	●	●
OCZ	OCZ3P1866C9LV6GK	6GB (3x 2GB)	DS	-	-	9-9-9	1.65	●	●	●
Patriot	PXD3421866ELK(XMP)	4GB (2x 2GB)	DS	-	-	9-9-9-24	1.65	●	●	●
Team	TXD32048M1866C9(XMP)	2GB	DS	Team	T3D1288RT-16	9-9-9-24	1.65	●	●	●

8 DIMM Slots

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.
-It is recommended to install the memory modules from the slots for better overclocking capability.
-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.